



English

TI-GGRAPH LINK™

FOR WINDOWS®

FOR THE TI-83

CONDENSED GUIDEBOOK

IBM is a registered trademark of International Business Machines Corporation.

Windows is a registered trademark of Microsoft Corporation.

Macintosh is a registered trademark of Apple Computer, Inc.

PostScript is a registered trademark of Adobe Systems, Inc.

© 1998 by Texas Instruments Incorporated. All Rights Reserved.

Contents

Getting Started with TI-GRAPH LINK for Windows	System Requirements.....	3
	Cable and Adapters	3
	Connecting the TI-GRAPH LINK Cable	4
	Installing the TI-GRAPH LINK Software	4
	Starting TI-GRAPH LINK and Testing the Connection	5
	Exiting the Program	5
	Receiving Files from a TI-83	6
	Sending Files to a TI-83	7
	Printing Opened TI-83 Files	8
	Printing Saved TI-83 Files	8
	Making a Memory Backup of a TI-83.....	9
	Sending a Memory Backup File to a TI-83.....	9
	Support and Service Information.....	10
	Warranty Information.....	11

Getting Started with TI-GRAPH LINK for Windows

System Requirements

The personal computer used to run TI-GRAPH LINK for Windows must meet the following hardware and software requirements:

Windows/Macintosh (Gray Cable)

- Microsoft Windows version 3.1 or later.
- MS-DOS® operating system version 3.1 or later (MS-DOS version 5.0 or later recommended).
- 486 PC or better with 8 MB available RAM.
- CD-ROM drive and one 3½-inch diskette drive.
- 256 color VGA.
- Hard disk with 1.5 MB available storage space.
- An available serial communication port configured as Com Port1, Com Port 2, Com Port 3, or Com Port 4.

Windows Only (Black Cable)

- Same as above plus 486 PC or better with 8 MB available RAM (Windows 95/98); 16 MB available RAM (Windows NT).

Cable and Adapters

The instructional package includes the following cable and adapter:

- One gray TI-GRAPH LINK cable that connects to a TI-83 and IBM-compatible computer.
- One 25-pin to 9-pin adapter.

The retail package includes the following cables:

- One black TI-GRAPH LINK cable that connects to an IBM-compatible computer.
- One unit-to-unit cable.

Connecting the TI-GRAPH LINK Cable

To connect the gray TI-GRAPH LINK cable between your PC and a TI-83:

1. Connect one end of the TI-GRAPH LINK cable to the PC serial port you will be using. If necessary, use the 25-pin to 9-pin adapter.
2. Connect the other end of the cable to the port at the bottom of the TI-83.
3. Insert all connectors firmly.

To connect the black TI-GRAPH LINK cable between your PC and a TI-83:

1. Connect the cable with the 9-pin connector to the PC serial port you will use. (If necessary, obtain a 9-pin to 25-pin adapter.)
2. Connect the other end of the black cable to one end of the unit-to-unit cable.
3. Connect the other end of the unit-to-unit cable to the port on the TI-83.
4. Insert all connectors firmly.

Installing the TI-GRAPH LINK Software

1. Start Microsoft Windows.
2. Insert the CD-ROM in your CD-ROM drive and follow the displayed instructions about installing the software.
 - Win 3.1x users need to run the TICD31 program from the TI Resource CD.
 - For 3½-inch diskette installations, proceed to step 3.
3. Assuming drive A is your 3½-inch drive, insert the TI-GRAPH LINK for Windows diskette in drive A.
4. For Windows 3.1x, from Program Manager, open the **File** menu and choose **Run**; for Windows 95, open the **Start** menu and choose **Run**.
5. Type **a:\TI83usa.exe**.

Note: Several TI-GRAPH LINK versions may include a character in the setup file name to identify the International or Americas version. You may need to verify the exact name of the setup file on the Windows diskette.

6. Press **Enter** and follow the instructions that appear on your display.

Starting TI-GRAPH LINK and Testing the Connection

1. Open the TI-GRAPH LINK group on the PC, and then double-click on a TI-83 program icon to start the application. The TI-83 Menu Bar, Keypad, and Edit window are displayed.
2. On the PC, open the **Link** menu and select the communication serial port (Com Port 1, Com Port 2, Com Port 3, or Com Port 4) to which the cable from a TI-83 is connected.
3. Open the **Link** menu to select the cable type: select **Windows/Macintosh** (Gray Cable) or **Windows Only** (Black Cable).
4. Open the **Link** menu. Select **Get Screen...**
5. Click on **Get Screen**. Ensure that TI-83 is on.

The contents of a TI-83 display appear in the window indicating that the communication link between a TI-83 and the PC is OK.

Note: If you obtain an error message when you click on **Get Screen**, there is a communications problem between the TI-83 and the PC.

- Make sure the TI-GRAPH LINK cable is connected to the correct serial communications port on the PC.
 - Make sure the correct cable type is selected in the **Link** menu.
 - Make sure all cable connectors are firmly inserted.
6. Click on **Done** to close the window.

Exiting the Program

You can close TI-GRAPH LINK in any of the following ways:

- Open the **File** menu and select **Exit**.
- Press **Alt+F** and then **X** on the PC keyboard.
- Double-click on the **Close** box in the upper-left corner of the screen.

Receiving Files from a TI-83

To receive items from a TI-83:

1. Open the **Link** menu and select **Receive....** After a few moments a window displays the data contents of the TI-83.
2. Select the item that you want to receive on the PC and click on **Add**. Repeat this step if you want to receive multiple items, or click on **Add All** to receive all listed TI-83 items.
3. (*Optional*) To receive the files to a group, click on **To Group** (☐ means individual files, ☒ means one group file).
4. Click on **OK** when you have selected all the files that you want to receive.
5. Select a directory on the PC in which you want to store the received TI-83 items.
6. Click on **Save** when you are ready to receive the files from a TI-83.
 - If **To Group** in step 3 is ☒, enter a new file name to replace the default name. Keep the file extension to remind you that this is a TI-83 group file.
 - If a TI-83 name contains special characters (such as α or β), TI-GGRAPH LINK prompts you to enter a substitute name for the file.
 - If an incoming TI-83 item has the same name as an existing file, you are prompted to overwrite, rename, skip to the next item, or cancel without receiving any more items.Select an option. Repeat as necessary until all items have been received.

7. Click on **OK** to return to the desktop display.

Sending Files to a TI-83

To send files from your PC to a TI-83:

1. Open the **Link** menu and select **Send....**

A window opens to display a list of TI-83 files. Go to the directory where your TI-83 files are located.

2. Select the file that you want to send to a TI-83 and click on **Add**. Repeat until all the files that you want to send are listed.

3. Click on **OK** to transmit the files.

A window displays a list of the files that were received by a TI-83.

- If a file from the PC has the same name as an existing TI-83 item, you are prompted to overwrite, rename, skip to the next item, or cancel without sending any more items.
- If a file is locked on the TI-83, you will be prompted to skip to the next item, rename the file, or quit without sending any more items.

Select an option. Repeat as necessary until all items have been sent to the TI-83.

4. Click on **OK** to return to the desktop display.

**Printing
Opened TI-83
Files**

To print a TI-83 program or data file that is displayed in an Edit or Data window:

1. Open the **File** menu and select **Open....** Go to the directory in which your TI-83 files are located.
2. Select the file that you want to print, then click on **OK** to open the file in an Edit or Data window.
3. Open the **File** menu and select **Print Document....**

The standard Windows Print dialogue box will open to let you select print options.

4. Click on **OK** to print the file.

**Printing Saved
TI-83 Files**

TI-GGRAPH LINK lets you print all saved TI-83 files except geometry figures and macros.

To print TI-83 program or data files:

1. Open the **File** menu, select **Print**. Go to the directory in which your TI-83 files are located.
2. Select the file that you want to print, then click on **OK**.

The Windows Print dialogue box will open to let you select print options.

3. Click on **OK** to print the file.

Making a Memory Backup of a TI-83

You can save a copy of the contents of a TI-83 memory to a PC file. Later, you can send the backup copy from the PC to a TI-83. You can also store a number of alternative memory copies on your PC. However, you cannot send a backup file to a TI-83 that was created with a different TI-83 software version.

To copy the entire contents of a TI-83 memory to a PC file:

1. Open the **Link** menu and select **Get Backup....**

The **Receive TI-83 Backup File** window opens.

After the entire backup has been received, the backup completion message is displayed.

2. Click on **Save** to write the backup file to the hard disk and return to the desktop display.

Sending a Memory Backup File to a TI-83

Warning! This operation overwrites the entire memory in a TI-83. All previous information in a TI-83 memory is replaced by the information from the backup file.

To send a memory backup file from the PC to a TI-83:

1. Open the **Link** menu, and select **Send Backup....**
2. Locate the directory where your TI-83 backup files (backup.83b) are located.
3. Select the backup file that you want to send to the TI-83 and click on **OK**.
4. A Warning window appears. Click on **OK** if you want to continue with the backup.
5. After the entire backup has been sent, click on **OK** to return to the desktop display.

Support and Service Information

Customers in the U.S., Canada, Puerto Rico, and the Virgin Islands

For general questions, contact Texas Instruments Customer Support:

phone: **1-800-TI-CARES (1-800-842-2737)**
e-mail: **ti-cares@ti.com**

For technical questions, call the Programming Assistance Group of Customer Support:

phone: **1-972-917-8324**

Customers outside the U.S., Canada, Puerto Rico, and the Virgin Islands

Contact TI by e-mail or visit the TI **calculator** home page on the World Wide Web.

e-mail: **ti-cares@ti.com**
Internet: **www.ti.com/calc**

Product Service

Customers in the U.S. and Canada Only

Always contact Texas Instruments Customer Support before returning a product for service.

Customers outside the U.S. and Canada

Refer to the leaflet enclosed with this product or contact your local Texas Instruments retailer/distributor.

Other TI Products and Services

Visit the TI **calculator** home page on the World Wide Web.

www.ti.com/calc

Refer to the leaflet enclosed with this product or contact your local Texas Instruments retailer/distributor.

Warranty Information

Customers in the U.S. and Canada Only

One-Year Limited Warranty for Electronic Product

This Texas Instruments (“TI”) electronic product warranty extends only to the original purchaser and user of the product.

Warranty Duration. This TI electronic product is warranted to the original purchaser for a period of one (1) year from the original purchase date.

Warranty Coverage. This TI electronic product is warranted against defective materials and construction. **THIS WARRANTY IS VOID IF THE PRODUCT HAS BEEN DAMAGED BY ACCIDENT OR UNREASONABLE USE, NEGLIGENCE, IMPROPER SERVICE, OR OTHER CAUSES NOT ARISING OUT OF DEFECTS IN MATERIALS OR CONSTRUCTION.**

Warranty Disclaimers. ANY IMPLIED WARRANTIES ARISING OUT OF THIS SALE, INCLUDING BUT NOT LIMITED TO THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, ARE LIMITED IN DURATION TO THE ABOVE ONE-YEAR PERIOD. TEXAS INSTRUMENTS SHALL NOT BE LIABLE FOR LOSS OF USE OF THE PRODUCT OR OTHER INCIDENTAL OR CONSEQUENTIAL COSTS, EXPENSES, OR DAMAGES INCURRED BY THE CONSUMER OR ANY OTHER USER.

Some states/provinces do not allow the exclusion or limitation of implied warranties or consequential damages, so the above limitations or exclusions may not apply to you.

Legal Remedies. This warranty gives you specific legal rights, and you may also have other rights that vary from state to state or province to province.

Warranty Performance. During the above one (1) year warranty period, your defective product will be either repaired or replaced with a reconditioned model of an equivalent quality (at TI’s option) when the product is returned, postage prepaid, to Texas Instruments Service Facility. The warranty of the repaired or replacement unit will continue for the warranty of the original unit or six (6) months, whichever is longer. Other than the postage requirement, no charge will be made for such repair and/or replacement. TI strongly recommends that you insure the product for value prior to mailing.

Software. Software is licensed, not sold. TI and its licensors do not warrant that the software will be free from errors or meet your specific requirements. **All software is provided “AS IS.”**

Copyright. The software and any documentation supplied with this product are protected by copyright.

All Customers Outside the U.S. and Canada

For information about the length and terms of the warranty, refer to your package and/or to the warranty statement enclosed with this product, or contact your local Texas Instruments retailer/distributor.